



All the music you want. All over your house.

Sonos ZonePlayer 120

ZP120



Wirelessly stream and amplify all your favourite music all over your house.

The Sonos® ZonePlayer™ 120 is amplified, wireless, compact, and convenient. With a state-of-the-art digital amplifier, the ZP120 works anywhere you've ever dreamed of having music — the bedroom, the bathroom or even the back garden. You can fill your house with ZP120s or mix and match with the non-amplified ZP90 for the ultimate in multi-room music.

Just plug the ZP120 in, connect your choice of speakers and you've got a room filled with music. And with the ZP120's expansive wireless range, you can play all your favourite songs and stations, all over the house. The design of the ZP120 is both compact and cool so you can hide it away or leave it out for all to see.

Key Features

- Superior sound with a powerful digital amplifier
- Best-in-class wireless technology for multi-room music
- Instant access to endless music
- Simple setup
- New features and music services with automatic updates

Sonos ZonePlayer 120



Superior sound with a powerful digital amplifier

The ZP120's state-of-the-art digital amplifier delivers audiophile-quality sound to any room. The energy-efficient Class D amplifier provides 55W per channel of power with a THD+N <.02% for excellent audio quality playback. And because the amplifier is built in, you won't need to connect to a stereo to play your music.



Best-in-class wireless technology for multi-room music

SonosNet™ 2.0, our latest wireless mesh network technology, provides double the wireless range* for whole-house coverage, ensures synchronous music playback, and avoids sources of wireless interference. All without a massive wiring project.



Instant access to endless music

Wherever there's a ZP120 and speakers (or any other ZonePlayer), you can listen to your personal collection of music stored on your computer, thousands of free Internet radio stations and millions of songs from the most popular online music services. You can also connect the ZP120 to an iPod or CD player and listen to those tunes throughout the house.



Simple setup

No technical or wiring expertise required. No need to break through walls or re-wire the house. A high-speed Internet connection and router are all you need. One ZonePlayer or ZoneBridge™ must be connected to the router and all the rest work wirelessly. Then add more ZonePlayers in more rooms without adding wires.



New features and music services with automatic updates

With free automatic software updates, you'll always have the newest features and music services to enjoy. Which means your system will keep getting better even after you buy.

*Based on a comparison between a site using only SonosNet 1.0 products versus a site using only SonosNet 2.0 products. Actual range will vary with site conditions.



TECHNICAL SPECIFICATIONS

Amplifier

Class-D

Rated output**

55W RMS continuous average power into 8 ohms, TDN+N<0.02%

Audio connections

RCA-type line-in (auto-detecting); RCA-type Subwoofer Out (auto-detecting), 80Hz crossover

Audio formats supported

Compressed MP3, WMA (including purchased Windows Media downloads), AAC (MPEG4), Ogg Vorbis, Audible (format 4), Apple Lossless, Flac (lossless) music files, as well as uncompressed WAV and AIFF files. Native support for 44.1kHz sample rates. See website for additional sample rates supported. *Apple "Fairplay" and WMA Lossless formats not currently supported.*

Music services supported

Napster® and downloads from any service offering DRM-free tracks

Operating systems (for stored files)

Windows® XP SP2 or higher, Windows Vista™, Mac OS X v10.4 and v10.5, Network Attached Storage devices supporting CIFS

Internet radio supported

Streaming MP3, WMA. Comes pre-loaded with 600+ stations

Wireless connectivity***

SonosNet™ 2.0, a secure AES encrypted, peer-to-peer wireless mesh network

Network bridging

The 2-port switch (10/100Mbps, auto MDI/MDIX) allows Ethernet devices to connect through SonosNet

Power supply

AC 100-240V, 50-60Hz, user-switchable

Dimensions/weight

3.5 x 7.3 x 8.15 in (89 x 185 x 207 mm)/5.1 lb (2.3 kg)

Operating/s storage temp.

32°F to 104°F (0°C to 40°C)/ -4°F to 158°F (-20°C to 70°C)

**Both channels driven, 22Hz-20KHZ-AES17 measurement bandwidth

***Internet connection required for access to Internet radio stations, online music services and software updates (DSL, cable modem or LAN-based high-speed Internet connection required.) Internet functionality may require payment of separate fee to a service provider.

Note: All specifications subject to change without notice.

